



Garage Door Restore
Sales, Service, Restorations

Purchase online at <https://garagedoorrestore.com.au/product/remotes/seip-remote-control-433-rc-am/>

Release the fixing screw at the rear center of the motor casing and open the hinged cover and proceed as follows :-

1. Locate the programming button on the decoder PCB inside the motor casing, (see photo below) and press it briefly (a LED will flash on the decoder PCB or a bleeping sound will be heard), you have 10 seconds to perform the next step.
2. Take the new handset and press the button that you wish to use to operate your door for one second.
3. Your new handset should now operate your garage door.
(Note: the Seip receiver modules type WAM1K & WAK1K have a small black programming button on the casing)

Clearing the memory - (recommended if a handset has been lost or stolen)
Refer to above but at step 1. press and hold the programming button for 20 seconds



Seip 433RC decoder module